

ZYXEL







Your Networking Ally



5G NR/4G LTE Cellular Routers

Quick Sales Guide

Mobile Broadband Product Portfolio

		5G NR	Cat. 18	Cat. 16
Outdoor	Router	NR7101 5G NR Outdoor Router 	LTE7490-M904 4G LTE-A Pro Outdoor Router 	LTE7480-S905 CBRS 4G LTE-A Outdoor Router 
	IAD		LTE5398-M904 4G LTE-A Pro Indoor IAD 	LTE5388-S905 CBRS 4G LTE-A Indoor IAD 
Indoor	Router			
Portable	Router	NR2101 5G NR Portable Router 		

Cat. 12

LTE7480-M804
4G LTE-A
Outdoor Router



Cat. 6

LTE7461-M602
4G LTE-A
Outdoor Router



LTE7460-M608
4G LTE-A
Outdoor Router



Cat. 4

LTE7240-M403
4G LTE
Outdoor Router



LTE5388-M804
4G LTE-A
Indoor IAD



LTE3316-M604
4G LTE-A
Indoor IAD



LTE4506-M606
4G LTE-A
HomeSpot



LTE3202-M430
4G LTE
Indoor Router



LTE3301-PLUS
4G LTE-A
Indoor Router













LTE1566-M634
4G LTE-A
Portable Router







WAH7601
4G LTE
Portable Router



Key Features

Product Category	Cat.	Model	Key Features
Outdoor CPE	5G NR	 NR7101	<ul style="list-style-type: none"> • 5G NR (Sub 6 GHz)/downlink 2.3 Gbps • IP67 Ingress Protection • Dual micro/3FF SIM card slot • TR-069 remote management • Mobile apps (iOS and Android)
	Cat. 18	 LTE7490-M904	<ul style="list-style-type: none"> • LTE Cat. 18/downlink 1.2 Gbps • IP68 Ingress Protection • 4 built-in high-gain antennas • TR-069 remote management • Mobile apps (iOS and Android)
	Cat. 16	 LTE7480-S905 CBRS	<ul style="list-style-type: none"> • LTE Cat. 16/downlink 580 Mbps (TDD config.2) • IP68 Ingress Protection • 4 built-in high-gain antennas • TR-069 remote management • Mobile apps (iOS and Android)
	Cat. 12	 LTE7480-M804	<ul style="list-style-type: none"> • LTE Cat. 12/downlink 600 Mbps • IP68 Ingress Protection • 4 built-in high-gain antennas • TR-069 remote management • Mobile apps (iOS and Android)
	Cat. 6	 LTE7461-M602	<ul style="list-style-type: none"> • LTE Cat. 6/downlink 300 Mbps • IP68 Ingress Protection • 2 built-in high-gain antennas • TR-069 remote management • Mobile apps (iOS and Android) • Supports North America frequency bands
		 LTE7460-M608	<ul style="list-style-type: none"> • LTE Cat. 6/downlink 300 Mbps • IP65 Ingress Protection • 2 built-in high-gain antennas • TR-069 remote management • Supports pan-European frequency bands
	Cat. 4	 LTE7240-M403	<ul style="list-style-type: none"> • LTE Cat. 4/downlink 150 Mbps • IP56 Ingress Protection • 2 built-in high-gain antennas • Passive Gigabit PoE LAN port • Supports mobile apps (iOS and Android)
Indoor CPE	Cat. 18	 LTE5398-M904	<ul style="list-style-type: none"> • LTE Cat. 18/downlink 1.2 Gbps • AC2050 dual-band WiFi AP • VoIP/VoLTE • LTE DL 4x4 MIMO B1/3/7 • Dual WAN failover (mobile WAN/Ethernet WAN) • TR-069 remote management
	Cat. 16	 LTE5388-S905 CBRS	<ul style="list-style-type: none"> • LTE CBRS Cat. 16/downlink 580 Mbps (TDD config.2) • AC2050 dual-band WiFi AP • VoIP/VoLTE • Dual WAN failover (mobile WAN/Ethernet WAN) • TR-069 remote management
	Cat. 12	 LTE5388-M804	<ul style="list-style-type: none"> • LTE Cat. 12/downlink 600 Mbps • AC2050 dual-band WiFi AP • VoIP/VoLTE • Dual WAN failover (mobile WAN/Ethernet WAN) • TR-069 remote management

Product Category	Cat.	Model	Key Features	
Indoor CPE	Cat. 6	LTE3316-M604	<ul style="list-style-type: none"> • LTE Cat. 6/downlink 300 Mbps • AC1200 dual-band WiFi AP • VoIP/VoLTE • 4 x GbE LAN ports (1 x WAN/3 x LAN) • Dual WAN failover (mobile WAN/Ethernet WAN) • TR-069 remote management 	
			LTE4506-M606	<ul style="list-style-type: none"> • Lightning-fast 4G LTE-A Cat. 6 with data rates of up to 300/50 Mbps (DL/UL) • Multi-mode, multi-band designs LTE FDD: B1/3/7/8/20 LTE TDD: B40 or B38 • AC1200 WLAN with 2 simultaneous SSIDs • One-touch WiFi sharing and supports up to 32 simultaneous WiFi clients
			LTE3301-PLUS	<ul style="list-style-type: none"> • LTE Cat. 6/downlink 300 Mbps • AC1200 dual-band WiFi AP • 4 x GbE LAN ports (1 x WAN/3 x LAN) • Dual WAN failover (mobile WAN/Ethernet WAN) • TR-069 remote management
		Cat. 4	LTE3202-M430	<ul style="list-style-type: none"> • Fast 4G LTE Cat. 4 connections of up to 150/50 Mbps (DL/UL) • Seamless switching among LTE/DC-HSPA+/EDGE • Supports LTE FDD B1/3/7/8/20/28, TDD B38/40, 3G B1/2/8, GSM B3/8 • 802.11n 300 Mbps WiFi with multiple SSIDs • Supports router or bridge modes, IPv4/IPv6 dual-stack
				

Product Category	Cat.	Model	Key Features
5G Portable Device	5G NR	NR2101	<ul style="list-style-type: none"> • 5G NR (Sub 6 GHz)/downlink 2.3 Gbps • AX1800 dual-band WiFi AP • Up to 10 hours working hours • 2.4" touch screen • One Gigabit RJ45 Ethernet LAN port
LTE Portable Devices	Cat. 6	LTE1566-M634	<ul style="list-style-type: none"> • LTE Cat. 6/downlink 300 Mbps • AC1200 dual-band WiFi AP, up to 32 WiFi clients • Up to 10 hours working hours • 2.4" TFT screen • Micro/3FF SIM card slot
	Cat. 4	WAH7601	<ul style="list-style-type: none"> • LTE Cat. 4/downlink 150 Mbps • Micro SD card slot (32 GB max.) • Supports Android and iOS apps • Up to 8 hours battery life (removable battery)
			

Frequency Band Comparison

5G NR

Model				5G NR	5G NR	
				NR7101	NR2101	
	Band	Freq (MHz)	Duplex			
5G NR	1	2100	FDD	Yes	Yes	
	3	1800	FDD	Yes	Yes	
	7	2600	FDD	Yes	Yes	
	8	900	FDD	Yes	Yes	
	20	800	FDD	Yes	Yes	
	28	700	FDD	Yes	Yes	
	41	2600	TDD	Yes	Yes	
	77	3700	TDD	Yes	Yes	
	78	3500	TDD	Yes	Yes	
	79	4500	TDD	Yes	Yes	
LTE	1	2100	FDD	Yes	Yes	
	3	1800	FDD	Yes	Yes	
	5	850	FDD	Yes	Yes	
	7	2600	FDD	Yes	Yes	
	8	900	FDD	Yes	Yes	
	20	800	FDD	Yes	Yes	
	28	700	FDD	Yes	Yes	
	38	2600	TDD	Yes	Yes	
	40	2300	TDD	Yes	Yes	
	41	2500	TDD	Yes	Yes	
	42	3500	TDD	Yes	Yes	
	43	3700	TDD	Yes	Yes	
	48	3600	TDD	-	Yes	
		DL CA			DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band DL 4xCA: intra-band and inter-band DL 5xCA: intra-band and inter-band within 4 bands	DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band DL 4xCA: intra-band and inter-band DL 5xCA: intra-band and inter-band within 4 bands
		UL CA			UL 2xCA: intra-band contiguous	UL 2xCA: intra-band contiguous
		DL 4x4 MIMO			B1/3/7/38/40/41/42/43	B1/3/7/38/40/41/42/43
		DL 256-QAM			Yes	Yes
		UL 64-QAM			Yes	Yes
		MIMO (UL/DL)			1x4	1x4
	3G	1	2100	FDD	Yes	Yes
2		900	FDD	-	Yes	
3		1800	FDD	Yes	Yes	
5		2100	FDD	Yes	Yes	
8		900	FDD	Yes	Yes	
WiFi AP	802.11n 2x2			Yes*	-	
	802.11ac 2x2			-	-	
	802.11ax 2x2			-	Yes	
	802.11ac 4x4			-	-	
	Number of users			-	up to 10	
Ethernet	GE LAN			x1 (PoE)	x1	
	GE WAN			-	-	
Phone	VoIP/VoLTE			-	-	
SIM slot	Micro/mini SIM slot			Micro SIM x2	Nano SIM	
Ingress protection	IP67			Yes	-	
Power	DC input			PoE 48 V	USB 5 V	
	Battery capacity			-	5300 mAh	

* WiFi AP is used for management purpose only

Portable

Model				Cat. 6	Cat. 4
				LTE1566-M634	WAH7601
LTE	Band	Freq (MHz)	Duplex	Personal	Personal
	1	2100	FDD	Yes	Yes
	2	1900	FDD	-	-
	3	1800	FDD	Yes	Yes
	5	850	FDD	-	-
	7	2600	FDD	Yes	Yes
	8	900	FDD	Yes	Yes
	20	800	FDD	Yes	Yes
	28	700	FDD	Yes (28a)	-
	38	2600	TDD	Yes	Yes
	40	2300	TDD	Yes	Yes
	41	2500	TDD	-	-
	42	3500	TDD	-	-
	43	3700	TDD	-	-
	48	3600	TDD	-	-
	DL CA		DL 2xCA: intra-band and inter-band	-	
3G	1	2100	FDD	Yes	Yes
	3	1800	FDD	Yes	-
	5	2100	FDD	-	-
	8	900	FDD	Yes	Yes
2G	2	1900	FDD	-	-
	3	1800	FDD	-	Yes
	5	850	FDD	-	-
	8	900	FDD	-	Yes
WiFi AP	802.11n 1x1			-	-
	802.11n 2x2			Yes	Yes
	802.11ac 2x2			Yes	-
	802.11ax 2x2			-	-
	Number of users			up to 10	up to 10
Battery capacity				3000 mAh	2000 mAh

Frequency Band Comparison

Outdoor CPE

Model				Cat. 18	Cat. 16
				LTE7490-M904	LTE7480-S905
Ingress Protection Rating				IP68	IP68
LTE	Band	Freq (MHz)	Duplex		
	1	2100	FDD	Yes	-
	2	1900	FDD	-	-
	3	1800	FDD	Yes	-
	4	1700	FDD	-	-
	5	850	FDD	Yes	-
	7	2600	FDD	Yes	-
	8	900	FDD	Yes	-
	12	700a	FDD	-	-
	13	700c	FDD	-	-
	20	800	FDD	Yes	-
	25	1900+	FDD	-	-
	26	850+	FDD	-	-
	28	700	FDD	Yes	-
	29	700d	FDD	-	-
	30	2300	FDD	-	-
	66	1700	FDD	-	-
	38	2600	TDD	Yes	-
	40	2300	TDD	Yes	-
	41	2500	TDD	Yes	-
	48	3600	TDD	-	Yes
		DL CA		DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band DL 4xCA: intra-band and inter-band DL 5xCA: intra-band and inter-band within 4 bands	DL 2xCA: intra-band DL 3xCA: intra-band DL 4xCA: intra-band
		UL CA		UL 2xCA: intra-band contiguous	UL 2xCA: intra-band
		DL 4x4 MIMO		B1/3/7	B48
		DL 256-QAM		Yes	Yes
		UL 64-QAM		Yes	Yes
		MIMO (UL/DL)		1x4	1x4
	3G	1	2100	FDD	Yes
2		900	FDD	-	-
3		1800	FDD	Yes	-
4		1700	FDD	-	-
5		2100	FDD	Yes	-
8		900	FDD	Yes	-
WiFi AP	802.11n 2x2			Yes*	Yes*
	802.11ac 2x2			-	-
	802.11ac 4x4			-	-
	Number of users			-	-
Ethernet	FE LAN			-	-
	GbE LAN			x1 (PoE)	x1 (PoE)
	GbE WAN			-	-
Phone	VoIP			-	-
	Vo3G/VoLTE			-	-
SIM slot	Micro/mini SIM slot		Micro SIM	Micro SIM	
Power	DC input		PoE 48 V	PoE 48 V	

* WiFi AP is used for management purpose only

Cat. 12	Cat. 6		
LTE7480-M804	LTE7461-M602	LTE7460-M608	LTE7240-M403
IP68	IP68	IP65	IP56
Yes	-	Yes	Yes
-	Yes	-	-
Yes	-	Yes	Yes
-	Yes	-	-
Yes	Yes	-	Yes
Yes	Yes	Yes	Yes
Yes	-	Yes	Yes
-	Yes	-	-
-	Yes	-	-
Yes	-	Yes	Yes
-	Yes	-	-
-	Yes	-	-
Yes	-	-	-
-	Yes	-	-
-	-	-	-
-	Yes	-	-
Yes	-	Yes	Yes
Yes	-	Yes	Yes
Yes	-	-	Yes
-	-	-	-
DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band	B2+B2/B5/B12/B13/B26/B29; B4+B4/B5/B12/B13/B26/B29; B7+B5/B7/B12/B13/B26/B29; B25+B5/B12/B13/B25/B26/B29; B66+B5/B12/B13/B26/B29/B66; (B29 is only for secondary component carrier)	B1+B3/B7 B1+B1/B8/B20 B3+B3/B7/B8/B20 B7+B7/B8/B20 B38+B38, B40+B40	-
UL 2xCA: intra-band contiguous	-	-	-
B1/3/7	-	-	-
Yes	-	-	-
Yes	-	-	-
1x4	1x2	1x2	1x2
Yes	-	Yes	Yes
-	Yes	-	-
Yes	-	-	-
-	Yes	-	-
Yes	Yes	-	Yes
Yes	-	Yes	Yes
Yes*	Yes*	-	Yes*
-	-	-	-
-	-	-	-
-	-	-	-
-	-	-	-
x1 (PoE)	x1 (PoE)	x1 (PoE)	x1 (passive PoE)
-	-	-	-
-	-	-	-
-	-	-	-
Micro SIM	Micro SIM	Mini SIM	Micro SIM
PoE 48 V	PoE 48 V	PoE 48 V	PoE 15 V

Frequency Band Comparison

Indoor CPE

Model				Cat. 18	Cat. 16	Cat. 12	
				LTE5398-M904	LTE5388-S905 CBRS	LTE5388-M804	
LTE	Band	Freq (MHz)	Duplex				
	1	2100	FDD	Yes	-	Yes	
	2	1900	FDD	-	-	-	
	3	1800	FDD	Yes	-	Yes	
	4	1700	FDD	-	-	-	
	5	850	FDD	Yes	-	Yes	
	7	2600	FDD	Yes	-	Yes	
	8	900	FDD	Yes	-	Yes	
	12	700a	FDD	-	-	-	
	13	700c	FDD	-	-	-	
	20	800	FDD	Yes	-	Yes	
	25	1900+	FDD	-	-	-	
	26	850+	FDD	-	-	-	
	28	700	FDD	Yes	-	Yes	
	29	700d	FDD	-	-	-	
	30	2300	FDD	-	-	-	
	66	1700	FDD	-	-	-	
	38	2600	TDD	Yes	-	Yes	
	40	2300	TDD	Yes	-	Yes	
	41	2500	TDD	Yes	-	Yes	
	48	3600	TDD	-	Yes	-	
		DL CA			DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band DL 4xCA: intra-band and inter-band DL 5xCA: intra-band and inter-band within 4 bands	DL 2xCA: intra-band DL 3xCA: intra-band DL 4xCA: intra-band	DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band
		UL CA			Intra-band contiguous	UL 2xCA: intra-band	Intra-band contiguous
		DL 4x4 MIMO			Yes	Yes	Yes
		DL 256-QAM			Yes	Yes	Yes
		UL 64-QAM			Yes	Yes	Yes
	MIMO (UL/DL)			1x4	1x4	1x4	
3G	1	2100	FDD	Yes	-	Yes	
	2	900	FDD	-	-	-	
	3	1800	FDD	Yes	-	Yes	
	4	1700	FDD	-	-	-	
	5	2100	FDD	Yes	-	Yes	
	8	900	FDD	Yes	-	Yes	
WiFi AP	802.11n 2x2			Yes	Yes	Yes	
	802.11ac 2x2			-	-	-	
	802.11ac 4x4			Yes	Yes	Yes	
	Number of users			up to 32	up to 32	up to 32	
Ethernet	FE LAN			-	-	-	
	GbE LAN			x2	x2	x2	
	GbE WAN			x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	
Phone	VoIP			x1 (optional)	x1 (optional)	x1 (optional)	
	Vo3G/VoLTE			x1 (optional)	x1 (optional)	x1 (optional)	
SIM slot	Micro/mini SIM slot			Micro SIM	Micro SIM	Micro SIM	
Power	DC input			DC 12 V	DC 12 V	DC 12 V	

Cat. 6			Cat. 4
LTE3316-M604	LTE3301-PLUS	LTE4506-M606 HomeSpot	LTE3202-M430
Yes	Yes	Yes	Yes
-	-	-	-
Yes	Yes	Yes	Yes
-	-	-	-
Yes	Yes	-	-
Yes	Yes	Yes	Yes
Yes	Yes	Yes	Yes
-	-	-	-
-	-	-	-
Yes	Yes	Yes	Yes
-	-	-	-
-	-	-	-
Yes	Yes	Yes	Yes (28a)
-	-	-	-
-	-	-	-
-	-	-	-
Yes	Yes	-	Yes
Yes	Yes	Yes	Yes
Yes	Yes	-	-
-	-	-	-
B1+B1/B5/B8/B20/B28 B3+B3/B5/B7/B8/B20/B28 B7+B5/B7/B8/B20/B28 B38+B38; B40+B40; B41+B41	B1+B1/B5/B8/B20/B28 B3+B3/B5/B7/B8/B20/B28 B7+B5/B7/B8/B20/B28 B38+B38; B40+B40; B41+B41	B1+B8 B3+B3/B7/B8/B20/B28 B7+B7/B20/B28 B40+B40 (B38+B38)	-
-	-	-	-
-	-	-	-
-	-	-	-
-	-	-	-
1x2	1x2	1x2	1x2
Yes	Yes	Yes	Yes
Yes	Yes	-	Yes
-	-	-	-
-	-	-	-
Yes	Yes	-	-
Yes	Yes	Yes	Yes
Yes	Yes	Yes	Yes
Yes	Yes	Yes	-
-	-	-	-
up to 32	up to 32	up to 32	up to 16
-	-	-	-
x4	x4	x1	x4
x1 (reuse LAN 1)	x1 (reuse LAN 1)	-	-
-	-	-	-
x1 (optional)	-	-	-
Micro SIM	Micro SIM	Micro SIM	Micro SIM
DC 12 V	DC 12 V	5 V micro USB port	DC 12 V

ZYXEL

Your Networking Ally

Corporate Headquarters

Zyxel Communications Corp.

Tel: +886-3-578-3942
Fax: +886-3-578-2439
Email: sales@zyxel.com.tw
http://www.zyxel.com

Europe

Zyxel Belarus

Tel: +375 17 334 6099
Fax: +375 17 334 5899
Email: sales@zyxel.by
http://www.zyxel.by

Zyxel BeNeLux

Tel: +31 23 555 3689
Fax: +31 23 557 8492
Email: sales@zyxel.nl
http://www.zyxel.nl
http://www.zyxel.be

Zyxel Bulgaria

(Bulgaria, Macedonia, Albania, Kosovo)
Tel: +3592 4443343
Email: info@cz.zyxel.com
http://www.zyxel.bg

Zyxel Czech Republic

Tel: +420 241 091 350
Hotline: +420 241 774 665
Fax: +420 241 091 359
Email: sales@cz.zyxel.com
http://www.zyxel.cz

Zyxel Denmark A/S

Tel: +45 39 55 07 00
Fax: +45 39 55 07 07
Email: sales@zyxel.dk
http://www.zyxel.dk

Zyxel Finland

Tel: +358 9 4780 8400
Email: myynti@zyxel.fi
http://www.zyxel.fi

Zyxel France

Tel: +33 (0)4 72 52 97 97
Fax: +33 (0)4 72 52 19 20
Email: info@zyxel.fr
http://www.zyxel.fr

Zyxel Germany GmbH

Tel: +49 (0) 2405-6909 0
Fax: +49 (0) 2405-6909 99
Email: sales@zyxel.de
http://www.zyxel.de

Zyxel Hungary & SEE

Tel: +36 1 848 0690
Email: info@zyxel.hu
http://www.zyxel.hu

Zyxel Iberia

Tel: +34 911 792 100
Email: ventas@zyxel.es
http://www.zyxel.es

Zyxel Italy

Tel: +39 011 2308000
Email: info@zyxel.it
http://www.zyxel.it

Zyxel Norway

Tel: +47 22 80 61 80
Fax: +47 22 80 61 81
Email: salg@zyxel.no
http://www.zyxel.no

Zyxel Poland

Tel: +48 223 338 250
Hotline: +48 226 521 626
Fax: +48 223 338 251
Email: info@pl.zyxel.com
http://www.zyxel.pl

Zyxel Romania

Tel: +40 31 0809 888
Fax: +40 31 0809 890
Email: info@cz.zyxel.com
http://www.zyxel.ro

Zyxel Russia

Tel: +7 (495) 539-9935
Fax: +7 (495) 542-8925
Email: info@zyxel.ru
http://www.zyxel.ru

Zyxel Slovakia

Tel: +421 220 861 847
Hotline: +421 220 861 848
Fax: +421 243 193 990
Email: info@cz.zyxel.com
http://www.zyxel.sk

Zyxel Sweden A/S

Tel: +46 8 55 77 60 60
Fax: +46 8 55 77 60 61
Email: sales@zyxel.se
http://www.zyxel.se

Zyxel Switzerland

Tel: +41 (0)44 806 51 00
Fax: +41 (0)44 806 52 00
Email: info@zyxel.ch
http://www.zyxel.ch

Zyxel Turkey A.S.

Tel: +90 212 314 18 00
Fax: +90 212 220 25 26
Email: bilgi@zyxel.com.tr
http://www.zyxel.com.tr

Zyxel UK Ltd.

Tel: +44 (0) 118 9121 700
Fax: +44 (0) 118 9797 277
Email: sales@zyxel.co.uk
http://www.zyxel.co.uk

Zyxel Ukraine

Tel: +380 (50) 440 88 61
Email: evelichko@zyxel.eu
http://www.zyxel.ua

Asia

Zyxel China (Shanghai) China Headquarters

Tel: +86-021-61199055
Fax: +86-021-52069033
Email: sales@zyxel.cn
http://www.zyxel.cn

Zyxel China (Beijing)

Tel: +86-010-62602249
Email: sales@zyxel.cn
http://www.zyxel.cn

Zyxel China (Tianjin)

Tel: +86-022-87890440
Fax: +86-022-87892304
Email: sales@zyxel.cn
http://www.zyxel.cn

Zyxel India

Tel: +91-11-4760-8800
Fax: +91-11-4052-3393
Email: info@zyxel.in
http://www.zyxel.in

Zyxel Kazakhstan

Tel: +7-727-2590-699
Fax: +7-727-2590-689
Email: info@zyxel.kz
http://www.zyxel.kz

Zyxel Korea Corp.

Tel: +82-2-890-5535
Fax: +82-2-890-5537
Email: sales@zyxel.kr
http://www.zyxel.kr

Zyxel Malaysia

Tel: +603 2282 1111
Fax: +603 2282 2611
Email: sales@zyxel.com.my
http://www.zyxel.com.my

Zyxel Middle East FZE

Tel: +971 4 372 4483
Cell: +971 562146416
Email: sales@zyxel-me.com
http://www.zyxel-me.com

Zyxel Philippine

Email: sales@zyxel.com.ph
http://www.zyxel.com.ph

Zyxel Singapore

Tel: +65 6339 3218
Hotline: +65 6339 1663
Fax: +65 6339 3318
Email: sales@zyxel.com.sg
http://www.zyxel.com.sg

Zyxel Taiwan (Taipei)

Tel: +886-2-2739-9889
Fax: +886-2-2735-3220
Email: sales_tw@zyxel.com.tw
http://www.zyxel.com.tw

Zyxel Thailand

Tel: +66-(0)-2831-5315
Fax: +66-(0)-2831-5395
Email: info@zyxel.co.th
http://www.zyxel.co.th

Zyxel Vietnam

Tel: (+848) 35202910
Fax: (+848) 35202800
Email: sales_vn@zyxel.com.tw
http://www.zyxel.com/vn/vi/

The Americas

Zyxel USA

North America Headquarters
Tel: +1-714-632-0882
Fax: +1-714-632-0858
Email: sales@zyxel.com
http://us.zyxel.com

Zyxel Brazil

Tel: +55 (11) 3373-7470
Fax: +55 (11) 3373-7510
Email: comercial@zyxel.com.br
http://www.zyxel.com/br/pt/

For more product information, visit us on the web at www.zyxel.com

Copyright © 2020 Zyxel Communications Corp. All rights reserved. Zyxel, Zyxel logo are registered trademarks of Zyxel Communications Corp. All other brands, product names, or trademarks mentioned are the property of their respective owners. All specifications are subject to change without notice.

